

**SYSTEM AND METHOD FOR FREQUENCY TRANSLATION USING AN IMAGE  
REJECT MIXER**

Kirk B. Ashby  
1607 Crown Point Road  
McKinney, TX 75070  
Citizenship: U.S.A.

Albert H. Taddiken  
1406 Red Oak Circle  
Farmersville, TX 75442  
Citizenship: U.S.A.

S. Vincent Birleson  
301 Lakeside Drive  
West Tawakoni, TX 75474  
Citizenship: U.S.A.

**TECHNICAL FIELD**

The present invention relates generally to the transmission of modulated signals and more particularly to the translation of a signal from one carrier frequency to another carrier frequency.

## BACKGROUND

The translation of modulated signals between different carrier frequencies is common in signal transmission. For example, upconverters are used in the television industry to translate information that is present at a particular low intermediate frequency (LIF) to a higher frequency for final transmission. Specifically, it is common in the United States to convert a signal at a LIF of 44 MHZ to a frequency division multiplex (FDM) final transmission frequency in the range of 53 MHZ to 857 MHZ. Similarly, European television transmission often utilizes up conversion of a signal at a LIF of 36.125 MHZ to a FDM final transmission frequency which may vary from a few tens of MHZ to nearly 1 GHz.

However, due to the relatively close packing of the FDM frequency bands associated with the various transmission channels, upconverters used as described above in the television industry are required to have a spectrally pure output so that information is transmitted in the desired FDM channel, without producing interfering signals in other FDM channels. Meeting the specifications generally required in the television industry is often very difficult due to the relatively close channelization scheme, the typically broad range of spectrum translated between, the relatively high transmission power requirements, the typically large amount of information modulated in the signal, and the like. For example, although often not providing the final transmission signal, upconverters are often deployed in the system such that their output signal must have enough output power to pass through a number of passive splitters and combiners that are disposed in the signal path. Upconverters used in these applications are not only required to translate a signal from one frequency to another within tight tolerances, but must also amplify the signal to a specified relatively high level.

Accordingly, the television industry presently uses upconverters that are designed using mostly discrete components, i.e., transistors, inductors, capacitors, resistors, deployed on printed circuit boards to provide discrete mixers, such as may be relatively easily relied upon to accommodate the relatively high transmission powers, provide the sharp cutoff filters needed to remove unacceptable spurious signals, and operate throughout the desired

frequency spread. However, the use of such components tends to result in an upconverter product which is large, expensive, and which consumes large amounts of power. For example, a typical state of the art upconverter providing head end quality for use in television transmission applications requires a 19 inch rack mount form factor. Such a size requirement significantly limits the situations in which the upconverter may be deployed. Moreover, the use of such discrete components generally results in relatively high power requirements, further limiting deployment opportunities.

Additional circuit limitations associated with the use of such discrete components further encumber the design and operation of prior art devices. For example, it is often very difficult and/or expensive to achieve good matching of components when utilizing discrete components. However, matching of components in order to implement particular circuit designs is often critical, e.g., as little as 1° of mismatch in certain circuit configurations introduce spurious signals that generally cannot be tolerated in the aforementioned television transmission applications. Accordingly, particular circuit designs are often precluded from use due to the difficulty and/or expense associated with suitably matching components to implement a circuit design.

Accordingly, a need exists in the art for a frequency translation function to be provided in a reduced form factor to reduce size, expense, and/or power consumption. A further need exists in the art to provide such frequency translation function in an integrated circuit or circuits to achieve the aforementioned reduced size, expense, and/or power consumption as well as to facilitate component matching and, therefore, broaden the circuit designs available for use in providing frequency translation functions.

## SUMMARY OF THE INVENTION

These and other objects, features and technical advantages are achieved by a system and method which utilizes an integrated circuit utilizing low cost filters to provide frequency translation in a low cost solution that occupies little space and consumes little power. A preferred embodiment upconverter architecture according to the present invention utilizes matching characteristics achievable in an integrated circuit design to implement image reject or single sideband mixers that relax the filter requirements of the circuit, such as the filter requirements of a high intermediate frequency (HIF), while providing frequency translation within the desired tolerances. Additionally, the preferred embodiment utilizes single sideband mixing to reduce the linearity requirements of components, such as amplifiers used in the frequency translation circuit.

A preferred embodiment of the present invention utilizes an integrated circuit design providing very close matching of particular circuit components in order to provide at least one single sideband mixer. Preferably this single sideband mixer utilizes a phase splitter providing in-phase (I) and quadrature (Q) components of a local oscillator (LO) frequency used in up conversion of a signal. Accordingly, a single substrate may be utilized according to the present invention to provide a fully integrated frequency translation circuit.

A most preferred embodiment of the present invention utilizes multiple stages of single sideband mixers in frequency translation. For example, a preferred embodiment utilizes a first single sideband mixer, preferably utilizing a corresponding first phase splitter, to translate a baseband or intermediate frequency (IF) input signal to a first IF. The first IF signal may be filtered and/or amplified, or otherwise manipulated as desired, before passing to a second single sideband mixer, preferably utilizing a corresponding second phase splitter, to translate the first IF to a second IF. Again the output of the second single sideband mixer stage may be filtered and/or amplified, or otherwise manipulated as desired, before being passed as an output signal.

According to a preferred embodiment of the present invention, the above described multiple stages of mixing utilized in frequency translation provide both frequency up

conversion and down conversion. For example, a most preferred embodiment utilizes the above described first mixing stage to up convert a baseband or IF signal to a high intermediate frequency (HIF) and the second mixing stage to down convert the HIF to a desired second IF which is at a lower frequency than the HIF. The use of up conversion and down conversion in frequency translation according to the present invention is preferred in order to simplify filtering of signals and, thereby, synergize the integrated configuration of the preferred embodiment upconverter.

It should be appreciated that because the preferred embodiment of the present invention utilizes single sideband mixing, images and other spurious signals associated with the input signal and/or first IF signal are eliminated or greatly reduced, such as on the order of -35 to -40 dB, and therefore the filtering requirements of the circuit are relaxed. Accordingly, a preferred embodiment of the present invention utilizes filter elements, such as bandpass, lowpass, and/or highpass filters, which are provided on a same single substrate as the preferred embodiment single sideband mixer. Although such integrated circuit filter elements typically do not provide as well defined cutoff points or as sharp of frequency rejection as is available with discrete filter elements, the preferred embodiment of the present invention may be relied upon to provide frequency translation to within tolerances associated with television transmission head end quality signals through the use of matched components and single sideband mixing. Of course, filter elements external to the preferred embodiment single substrate, such as discrete filter elements, may be utilized if desired.

Additionally, high output signal quality is achievable according to the present invention utilizing active components, such as amplifiers, having relaxed linearity requirements. Utilizing the single sideband mixers of the preferred embodiment greatly reduces the signal images and other spurious signals which often cause a circuit design to implement highly linear active components in order to avoid subsequent distortion of the signals. However, the design of a preferred embodiment of the present invention relies upon active components which are linear over a smaller range of frequencies and signal levels due to the elimination and/or reduction of spurious signals. Accordingly, implementation of such

active components on the same single substrate as the preferred embodiment single sideband mixers may be easily accomplished to thereby further synergize the integrated configuration of the preferred embodiment upconverter.

5 A technical advantage of the present invention is realized in providing frequency translation functions in an integrated circuit form factor. Further technical advantages are provided in the reduced size, expense, and power consumption associated with implementation in an integrated circuit form factor.

10 The foregoing has outlined rather broadly the features and technical advantages of the present invention in order that the detailed description of the invention that follows may be better understood. Additional features and advantages of the invention will be described hereinafter which form the subject of the claims of the invention. It should be appreciated by those skilled in the art that the conception and specific embodiment disclosed may be readily utilized as a basis for modifying or designing other structures for carrying out the same purposes of the present invention. It should also be realized by those skilled in the art that 15 such equivalent constructions do not depart from the spirit and scope of the invention as set forth in the appended claims.

## BRIEF DESCRIPTION OF THE DRAWING

For a more complete understanding of the present invention, and the advantages thereof, reference is now made to the following descriptions taken in conjunction with the accompanying drawing, in which:

- 5           FIGURE 1 shows a block diagram of a typical prior art upconverter circuit; and
- FIGURE 2 shows a block diagram of a preferred embodiment frequency translation circuit.

## DETAILED DESCRIPTION

In understanding the present invention it is helpful to understand the current state of the art with respect to upconverter solutions. Directing attention to FIGURE 1, a block diagram of a typical prior art upconverter solution is shown. The upconverter circuitry of FIGURE 1 is often utilized in providing up conversion of a low intermediate frequency (LIF) video signal, such as might be provided by a video signal modulated at approximately 44 MHZ in the United States or approximately 36 MHZ in Europe, to frequencies associated with particular television channels, such as may be defined in the spectrum from approximately 53 MHZ to approximately 857 MHZ.

In the architecture of FIGURE 1, amplifier 111 is provided to amplify the input signal to a desired level prior to frequency translation. Although not illustrated, according to some prior art solutions amplifier 111 may be a variable gain amplifier which is operated to maintain the input to mixer 121 at a constant magnitude.

Mixer 121 is provided to convert the input signal frequency, to a high intermediate frequency (HIF) utilizing local oscillator (LO) 131. Amplifier 112 is provided to amplify the HIF signal, such as to compensate for losses associated with mixer 121 or to otherwise amplify the HIF signal to a desired HIF output level. Because of the images and other spurious signals associated with the HIF signal as provided by mixer 121, amplifier 112 is typically a highly linear component in order to avoid distortion of the amplified signals.

Filter 141 is a bandpass filter utilized to filter the HIF signal to remove the images and other undesired spurious signals. In order to sufficiently filter the spurious signals associated with mixing the input signal with the carrier provided by LO 131, filter 141 must typically provide very sharp pass band cutoffs. Amplifier 113 is provided to amplify the filtered HIF signal, such as to compensate for filter losses, prior to final conversion to a desired frequency via mixer 122.



Mixer 122 is provided to convert the HIF signal frequency to a desired output frequency signal utilizing LO 132. In order to provide selection of a desired output channel of a frequency division set of channels, LO 132 may be a variable oscillator as shown.

Amplifier 114 is provided to amplify the selected output frequency signal to a desired output signal level. As illustrated, amplifier 114 may be a variable gain amplifier to provide selection of a desired output signal level. Because of the images and other spurious signals associated with the output signal as provided by mixer 122, amplifier 114 is typically a highly linear component in order to avoid distortion of the amplified signals. Moreover, although illustrated in FIGURE 1 as a single circuit element, often amplification provided at the output stage of typical prior art upconverters is provided by a combination of one or more fixed gain amplifiers and a variable attenuator.

Filter 142 is may be a variable frequency filter utilized to suppress undesired spurious signals on either side of the desired output signal frequency. As with filter 141 discussed above, filter 142 is a bandpass filter which, in order to sufficiently filter the spurious signals associated with mixing the HIF signal with the carrier provided by LO 132, must typically provide very sharp pass band cutoffs.

Alternatively, the filtering function of filter 142 may be provided by a bank of filters where the filters of the bank filter different frequency ranges. Accordingly, depending upon the desired frequency of the output signal, a particular filter or filters may be switched in the output signal path to provide the desired filtering. However, such an embodiment adds to the size and expense of the resulting upconverter solution.

It should be appreciated that in the prior art, the above described elements are provided by discrete components in order to accommodate the desired frequency ranges and power levels, as well as to provide an output signal of a desired quality.

In order to better understand limitations of the prior art circuitry of FIGURE 1, assume that the input signal is provided at a frequency of  $f_{LIF}$  and that it is desired to provide an HIF signal from mixer 121 at a frequency of  $f_{LO1} + f_{LIF}$ . Mixer 121 will not only provide

output of an HIF signal at frequency  $f_{LO1}+f_{LIF}$ , but will also provide an image signal at frequency  $f_{LO1}-f_{LIF}$ . This image signal will approximately be of the same magnitude as the desired HIF signal at frequency  $f_{LO1}+f_{LIF}$ . Additionally, because of the physical limitations of mixer 121 result in signal leakage, some of the carrier signal  $f_{LO1}$  will also be present in the output of mixer 121. However, the carrier power level of the carrier signal  $f_{LO1}$  will typically be on the order of 20 dB below the desired HIF signal level in video up conversion implementations.

In meeting video head end signal quality requirements, the power levels of the above identified spurious signals must be at least 60 dB below (-60 dBc) the power level of the desired signal. Accordingly, filter 141 must attenuate the unwanted image ( $f_{LO1}-f_{LIF}$ ) by 60 dB or more and the leaking carrier signal ( $f_{LO1}$ ) by 40 dB or more. If filter 141 does not provide sufficient filtering of these spurious signals they will be passed on to mixer 122 and converted, resulting in not only the original spurious signals but also additional spurious signals spawned therefrom. Accordingly, in such a situation filter 142 is not only required to provide filtering sufficient to supplement that provided by filter 141, but must also provide filtering sufficient to redress the additional spurious signals as well as the spurious signals (i.e.,  $f_{LO2}+f_{HIF}$  and  $f_{LO2}$ ) associated with mixer 122. Accordingly, the filtering requirements of filter 142 may be substantial. Moreover, where the output frequency is variable, the center frequency of filter 142 must be correspondingly variable. The provision of a variable filter meeting such requirements results in added size, complexity, and cost to the upconverter solution.

Further problems are present in the prior art circuitry of FIGURE 1 with respect to the amplification of the output signal. Assuming that the HIF signal is at the frequency  $f_{HIF}$ , mixer 122 will produce both a desired output at  $f_{LO2}-f_{HIF}$  and an undesired image at frequency  $f_{LO2}+f_{HIF}$ , as well as a carrier leakage signal at frequency  $f_{LO2}$ . If  $f_{LO1}$  and  $f_{LO2}$  are chosen properly, the undesired image signal at frequency  $f_{LO2}+f_{HIF}$  will be out of the band of interest and will not be a direct interferer. However, this undesired image signal will pose problems for amplifier 114.

As discussed above, both the desired signal at frequency  $f_{LO2}-f_{HIF}$  and the undesired image at frequency  $f_{LO2}+f_{HIF}$  provided by mixer 122 will be of substantially the same magnitude. Accordingly, the peak signal value in amplifier 114 will be approximately twice as large as it would be if only the desired output signal at frequency  $f_{LO2}-f_{HIF}$  were provided thereto. Therefore, in order to maintain the linearity required by the system, amplifier 114 must consume much more power than would be needed if only the actual signal of interest were present and amplified. Moreover, although the above discussion is provided with reference to amplifier 114, it should be appreciated that similar problems are associated with amplifier 112. For example, the desired circuit gain may be distributed over the various amplifiers, such as amplifiers 112, 113, and 114, thereby resulting in appreciably high gain requirements and the power consumption problems discussed above with respect to amplifier 114.

Directing attention to FIGURE 2, a preferred embodiment signal translator 200 of the present invention is shown which accommodates a relatively broad frequency range of output signals as well as provides relatively high output signal power levels. Specifically, the preferred embodiment signal translator 200 of FIGURE 2 is adapted to provide frequency up conversion in a range of frequencies compatible with the spectrum of television channels typically used throughout the United States and Europe at a power level sufficient for use in television signal transmission systems such as cable television head end system. Moreover, the circuitry of the preferred embodiment is configured to utilize integrated components such that a synergistic cascade of component attributes provides an output signal having a desired signal quality, such as a signal quality meeting video transmission head end requirements.

In the preferred embodiment circuitry of FIGURE 2, amplifier 211 preferably acts as an input buffer and/or provides a portion of the total system gain. Alternative embodiments of the present invention may omit amplifier 211 and/or utilize other components to provide desired signal conditioning attributes, such as a filter or attenuator element.

The signal output from amplifier 211 is provided to phase shifter 251. Phase shifter 251 provides splitting of signals provided thereto, adjusting their relative phase to thereby

provide signal components having a predetermined phase relationship with respect to each other. Preferably, phase shifter 251 provides in-phase (I) and quadrature (Q) signal components (providing a 90° phase difference), although other phase relationships may be utilized according to the present invention.

5 Each of the signal components provided by phase shifter 251 is translated to a desired frequency through the use of an associated mixer, here mixer 221 and mixer 222. However, as LO 231 providing the carrier frequency clock utilized by both mixer 221 and mixer 222 is also provided to a phase shifter, shown as phase shifter 252, the carriers driving mixer 221 and mixer 222 are out of phase a predetermined amount, although operating at a same frequency. According to the preferred embodiment, the carrier signal components provided by phase shifter 252 are in-phase and quadrature carrier signal components, although other phase relationships may be utilized according to the present invention.

10 It should be appreciated that each of mixers 221 and 222 operate to provide both a desired signal and an image of the signal component provided thereto. However, the signal components provided to each of mixers 221 and 222 are out of phase a predetermined amount. Moreover, the carrier signal components provided each of mixers 221 and 222 are out of phase a predetermined amount. Accordingly, by utilizing these phase differences the signal components may be provided to mixers 221 and 222 in such a way as to result in constructive combining of desired signals and destructive combining of undesired signal  
15 images. Specifically, when the outputs of mixers 221 and 222 are summed by summer 261, the desired signal components are in-phase and constructively combine while the undesired images are out of phase and destructively combine. For example, according to the preferred embodiment of FIGURE 2, assuming the input signal is at a frequency of  $f_{LIF}$ , the desired signal components  $f_{LO1} + f_{LIF}$  from each mixers 221 and 222 are in-phase and combine to  
20 enhance the amplitude of the resulting HIF signal while the undesired signal image components  $f_{LO1} - f_{LIF}$  from mixers 221 and 222 are 180° out of phase and combine to substantially null the image signals. Accordingly, as only the desired signal is output and the undesired signal images at the other sideband are suppressed, phase shifters 251 and 252,

mixers 221 and 222, and summer 261 form a single sideband (SSB) or image reject mixer (SSB mixer 201).

In using an integrated circuit to implement the preferred embodiment of the present invention, double balanced mixers having very good carrier suppression can be implemented relatively easily. Accordingly, it is possible, through proper matching of components, to achieve a sideband suppression of approximately 40 dB relative to the desired signal in an integrated circuit implementation of the above described SSB mixer 201. Even with the rather high isolation between signal and spurious signals of 60 dB required in video head end application, the filtering requirements of the preferred embodiment circuitry of FIGURE 2 may be relaxed. For example, assuming 40 dBc of image suppression, a filter providing an additional 20 dB of filtering may be relied upon to provide the desired level of signal quality. Such a filter may be implemented at a relatively low cost and in a relatively small footprint, such as upon the same substrate as the SSB mixer.

Referring still to FIGURE 2, the output of SSB mixer 201, referred to herein as the HIF signal, is preferably provided to amplifier 212. In the preferred embodiment amplifier 212 provides a portion of the total circuit gain and/or provides the HIF signal at a desired magnitude for filtering by filter 241. Alternative embodiments of the present invention may omit amplifier 212 and/or utilize other components to provide desired signal conditioning attributes.

Filter 241 of the preferred embodiment is a bandpass filter having a center frequency corresponding to the HIF signal frequency. However, as should be appreciated from the above discussion, the particular implementation of filter 241 may provide substantially less selectivity than is typically provided in a frequency translation circuit providing similar signal qualities. This is because the preferred embodiment implementation utilizes component matching to provide a high degree of image suppression, thus negating the need for a sharp cutoff filter. Synergism is provided by the preferred embodiment configuration in that such a filter may be implemented on the same substrate as the SSB mixer of the preferred embodiment without compromising a desired level of signal quality. However, this filter

may be provided externally to a common substrate utilized for a majority of the remaining circuit elements of a preferred embodiment frequency translator 200. It should be appreciated that advantages are still realized in such an alternative embodiment utilizing an external filter as the selectivity requirements of the filter remain relaxed, and thus the complexity and/or cost, of this filter is reduced. Moreover, it should also be appreciated that, where the level of image rejection provided by SSB mixer 201 provides a desired level of signal quality, filter 241 may be omitted, if desired.

In the preferred embodiment of FIGURE 2, amplifier 213 is provided at the second frequency translation stage to act as an input buffer and/or provides a portion of the total system gain. Alternative embodiments of the present invention may omit amplifier 213 and/or utilize other components to provide desired signal conditioning attributes.

According to the preferred embodiment, a second SSB mixer, SSB mixer 202 comprising phase shifters 253 and 254, mixers 223 and 224, and summer 262, is provided to down convert the HIF signal to a desired output frequency, such as may correspond to a desired television frequency division channel. Accordingly, similar to SSB mixer 201 discussed above, the signal output from amplifier 213 is provided to phase shifter 253. Phase shifter 253 provides splitting of signals provided thereto, adjusting their relative phase to thereby provide signal components having a predetermined phase relationship with respect to each other. Preferably, phase shifter 253 provides I and Q signal components, although other phase relationships may be utilized according to the present invention.

Each of the signal components provided by phase shifter 253 is translated to a desired frequency through the use of an associated mixer, here mixer 223 and mixer 224. However, as LO 232 providing the carrier frequency clock utilized by both mixer 223 and mixer 224 is also provided to a phase shifter, shown as phase shifter 254, the carriers driving mixer 223 and mixer 224 are out of phase a predetermined amount, although operating at a same frequency. According to the preferred embodiment, the carrier signal components provided by phase shifter 254 are in-phase and quadrature carrier signal components, although other phase relationships may be utilized according to the present invention.

As described in detail above with respect to SSB mixer 201, SSB mixer 202 utilizes the phase differences the signal components to result in constructive signal and destructive signal image combining at summer 262. Accordingly, SSB mixer 202 is used to reduce the magnitude of the undesired image at frequency  $f_{LO2}+f_{HIF}$ , assuming frequency  $f_{HIF}$  is the frequency of the desired signal at the high intermediate frequency, while enhancing the desired signal at frequency  $f_{LO2}-f_{HIF}$ .

It should be appreciated that LO 232 is illustrated as a variable oscillator, such as may be implemented in the form of a voltage controlled oscillator. Accordingly, SSB mixer 202 may be controlled to translate an input signal at  $f_{HIF}$  to any of a plurality of output signal frequencies, such as may correspond to particular defined channel frequencies. Additionally or alternatively, LO 232 may be controlled so as to provide a frequency hopping scheme suitable for deterring useful interception of a transmitted signal and/or for use in multiplexing a signal or plurality of signals, such as in time division bursts, on various output frequencies.

Amplifier 214 is provided to manipulate the amplitude of the signal provided from SSB mixer 202. Preferably amplifier 214 is utilized to provide the final amount of circuit gain to the signal output by frequency translator 200. Although illustrated as a single circuit element, amplifier 214 may be implemented as a combination of various gain stages. It should be appreciated that amplifier 214 is shown as a variable gain amplifier, such as may be useful in providing an output signal at a controllable magnitude. However, fixed gain amplifiers may be utilized according to the present invention. Additionally, where no gain adjustment is desired, amplifier 214 may be omitted, if desired.

It should be appreciated that the SSB mixers of the preferred embodiment of the present invention substantially reduce or eliminate the image signals associated with translation of the signal. Accordingly, rather than being provided two signals as in the prior art circuitry of FIGURE 1, amplifier 214 is substantially provided only the desired signal. Accordingly, as there is only one signal provided to amplifier 214, the linearity requirements of this amplifier are substantially relaxed. For example, when multiple signals at different frequencies are present they can intermodulate, with each other and create unwanted spurious

signals so the linearity becomes very crucial. However, by reducing the amplitude of the unwanted image, output amplifier of the present invention does not have that intermodulation, thus significantly relaxing the linearity requirements and thereby making implementation of the amplifier easier. Moreover, the presence of substantially a single  
5 signal results in less power being consumed in signal amplification by amplifier 214. Accordingly, such an amplifier may be implemented on a same substrate as all or substantially all of the circuit elements of frequency translator 200 shown in FIGURE 2.

The preferred embodiment of FIGURE 2 includes filter 242 in the output signal path. According to this preferred embodiment the filter is an adjustable frequency filter that may be adjusted to a particular center frequency corresponding to adjustment of LO 232. Accordingly, filter 242 may be utilized for additional filtering of spurious signals if desired. However, because the mixers utilized by the preferred embodiment of the present invention provide a high level of sideband signal rejection, filter 242 may be implemented with a lesser degree of selectivity than that of prior art upconverter solutions. Moreover, alternative  
10 15 20 25 30 35 40 45 50 55 60 65 70 75 80 85 90 95 100 105 110 115 120 125 130 135 140 145 150 155 160 165 170 175 180 185 190 195 200 205 210 215 220 225 230 235 240 245 250 255 260 265 270 275 280 285 290 295 300 305 310 315 320 325 330 335 340 345 350 355 360 365 370 375 380 385 390 395 400 405 410 415 420 425 430 435 440 445 450 455 460 465 470 475 480 485 490 495 500 505 510 515 520 525 530 535 540 545 550 555 560 565 570 575 580 585 590 595 600 605 610 615 620 625 630 635 640 645 650 655 660 665 670 675 680 685 690 695 700 705 710 715 720 725 730 735 740 745 750 755 760 765 770 775 780 785 790 795 800 805 810 815 820 825 830 835 840 845 850 855 860 865 870 875 880 885 890 895 900 905 910 915 920 925 930 935 940 945 950 955 960 965 970 975 980 985 990 995 1000 1005 1010 1015 1020 1025 1030 1035 1040 1045 1050 1055 1060 1065 1070 1075 1080 1085 1090 1095 1100 1105 1110 1115 1120 1125 1130 1135 1140 1145 1150 1155 1160 1165 1170 1175 1180 1185 1190 1195 1200 1205 1210 1215 1220 1225 1230 1235 1240 1245 1250 1255 1260 1265 1270 1275 1280 1285 1290 1295 1300 1305 1310 1315 1320 1325 1330 1335 1340 1345 1350 1355 1360 1365 1370 1375 1380 1385 1390 1395 1400 1405 1410 1415 1420 1425 1430 1435 1440 1445 1450 1455 1460 1465 1470 1475 1480 1485 1490 1495 1500 1505 1510 1515 1520 1525 1530 1535 1540 1545 1550 1555 1560 1565 1570 1575 1580 1585 1590 1595 1600 1605 1610 1615 1620 1625 1630 1635 1640 1645 1650 1655 1660 1665 1670 1675 1680 1685 1690 1695 1700 1705 1710 1715 1720 1725 1730 1735 1740 1745 1750 1755 1760 1765 1770 1775 1780 1785 1790 1795 1800 1805 1810 1815 1820 1825 1830 1835 1840 1845 1850 1855 1860 1865 1870 1875 1880 1885 1890 1895 1900 1905 1910 1915 1920 1925 1930 1935 1940 1945 1950 1955 1960 1965 1970 1975 1980 1985 1990 1995 2000 2005 2010 2015 2020 2025 2030 2035 2040 2045 2050 2055 2060 2065 2070 2075 2080 2085 2090 2095 2100 2105 2110 2115 2120 2125 2130 2135 2140 2145 2150 2155 2160 2165 2170 2175 2180 2185 2190 2195 2200 2205 2210 2215 2220 2225 2230 2235 2240 2245 2250 2255 2260 2265 2270 2275 2280 2285 2290 2295 2300 2305 2310 2315 2320 2325 2330 2335 2340 2345 2350 2355 2360 2365 2370 2375 2380 2385 2390 2395 2400 2405 2410 2415 2420 2425 2430 2435 2440 2445 2450 2455 2460 2465 2470 2475 2480 2485 2490 2495 2500 2505 2510 2515 2520 2525 2530 2535 2540 2545 2550 2555 2560 2565 2570 2575 2580 2585 2590 2595 2600 2605 2610 2615 2620 2625 2630 2635 2640 2645 2650 2655 2660 2665 2670 2675 2680 2685 2690 2695 2700 2705 2710 2715 2720 2725 2730 2735 2740 2745 2750 2755 2760 2765 2770 2775 2780 2785 2790 2795 2800 2805 2810 2815 2820 2825 2830 2835 2840 2845 2850 2855 2860 2865 2870 2875 2880 2885 2890 2895 2900 2905 2910 2915 2920 2925 2930 2935 2940 2945 2950 2955 2960 2965 2970 2975 2980 2985 2990 2995 3000 3005 3010 3015 3020 3025 3030 3035 3040 3045 3050 3055 3060 3065 3070 3075 3080 3085 3090 3095 3100 3105 3110 3115 3120 3125 3130 3135 3140 3145 3150 3155 3160 3165 3170 3175 3180 3185 3190 3195 3200 3205 3210 3215 3220 3225 3230 3235 3240 3245 3250 3255 3260 3265 3270 3275 3280 3285 3290 3295 3300 3305 3310 3315 3320 3325 3330 3335 3340 3345 3350 3355 3360 3365 3370 3375 3380 3385 3390 3395 3400 3405 3410 3415 3420 3425 3430 3435 3440 3445 3450 3455 3460 3465 3470 3475 3480 3485 3490 3495 3500 3505 3510 3515 3520 3525 3530 3535 3540 3545 3550 3555 3560 3565 3570 3575 3580 3585 3590 3595 3600 3605 3610 3615 3620 3625 3630 3635 3640 3645 3650 3655 3660 3665 3670 3675 3680 3685 3690 3695 3700 3705 3710 3715 3720 3725 3730 3735 3740 3745 3750 3755 3760 3765 3770 3775 3780 3785 3790 3795 3800 3805 3810 3815 3820 3825 3830 3835 3840 3845 3850 3855 3860 3865 3870 3875 3880 3885 3890 3895 3900 3905 3910 3915 3920 3925 3930 3935 3940 3945 3950 3955 3960 3965 3970 3975 3980 3985 3990 3995 4000 4005 4010 4015 4020 4025 4030 4035 4040 4045 4050 4055 4060 4065 4070 4075 4080 4085 4090 4095 4100 4105 4110 4115 4120 4125 4130 4135 4140 4145 4150 4155 4160 4165 4170 4175 4180 4185 4190 4195 4200 4205 4210 4215 4220 4225 4230 4235 4240 4245 4250 4255 4260 4265 4270 4275 4280 4285 4290 4295 4300 4305 4310 4315 4320 4325 4330 4335 4340 4345 4350 4355 4360 4365 4370 4375 4380 4385 4390 4395 4400 4405 4410 4415 4420 4425 4430 4435 4440 4445 4450 4455 4460 4465 4470 4475 4480 4485 4490 4495 4500 4505 4510 4515 4520 4525 4530 4535 4540 4545 4550 4555 4560 4565 4570 4575 4580 4585 4590 4595 4600 4605 4610 4615 4620 4625 4630 4635 4640 4645 4650 4655 4660 4665 4670 4675 4680 4685 4690 4695 4700 4705 4710 4715 4720 4725 4730 4735 4740 4745 4750 4755 4760 4765 4770 4775 4780 4785 4790 4795 4800 4805 4810 4815 4820 4825 4830 4835 4840 4845 4850 4855 4860 4865 4870 4875 4880 4885 4890 4895 4900 4905 4910 4915 4920 4925 4930 4935 4940 4945 4950 4955 4960 4965 4970 4975 4980 4985 4990 4995 5000 5005 5010 5015 5020 5025 5030 5035 5040 5045 5050 5055 5060 5065 5070 5075 5080 5085 5090 5095 5100 5105 5110 5115 5120 5125 5130 5135 5140 5145 5150 5155 5160 5165 5170 5175 5180 5185 5190 5195 5200 5205 5210 5215 5220 5225 5230 5235 5240 5245 5250 5255 5260 5265 5270 5275 5280 5285 5290 5295 5300 5305 5310 5315 5320 5325 5330 5335 5340 5345 5350 5355 5360 5365 5370 5375 5380 5385 5390 5395 5400 5405 5410 5415 5420 5425 5430 5435 5440 5445 5450 5455 5460 5465 5470 5475 5480 5485 5490 5495 5500 5505 5510 5515 5520 5525 5530 5535 5540 5545 5550 5555 5560 5565 5570 5575 5580 5585 5590 5595 5600 5605 5610 5615 5620 5625 5630 5635 5640 5645 5650 5655 5660 5665 5670 5675 5680 5685 5690 5695 5700 5705 5710 5715 5720 5725 5730 5735 5740 5745 5750 5755 5760 5765 5770 5775 5780 5785 5790 5795 5800 5805 5810 5815 5820 5825 5830 5835 5840 5845 5850 5855 5860 5865 5870 5875 5880 5885 5890 5895 5900 5905 5910 5915 5920 5925 5930 5935 5940 5945 5950 5955 5960 5965 5970 5975 5980 5985 5990 5995 6000 6005 6010 6015 6020 6025 6030 6035 6040 6045 6050 6055 6060 6065 6070 6075 6080 6085 6090 6095 6100 6105 6110 6115 6120 6125 6130 6135 6140 6145 6150 6155 6160 6165 6170 6175 6180 6185 6190 6195 6200 6205 6210 6215 6220 6225 6230 6235 6240 6245 6250 6255 6260 6265 6270 6275 6280 6285 6290 6295 6300 6305 6310 6315 6320 6325 6330 6335 6340 6345 6350 6355 6360 6365 6370 6375 6380 6385 6390 6395 6400 6405 6410 6415 6420 6425 6430 6435 6440 6445 6450 6455 6460 6465 6470 6475 6480 6485 6490 6495 6500 6505 6510 6515 6520 6525 6530 6535 6540 6545 6550 6555 6560 6565 6570 6575 6580 6585 6590 6595 6600 6605 6610 6615 6620 6625 6630 6635 6640 6645 6650 6655 6660 6665 6670 6675 6680 6685 6690 6695 6700 6705 6710 6715 6720 6725 6730 6735 6740 6745 6750 6755 6760 6765 6770 6775 6780 6785 6790 6795 6800 6805 6810 6815 6820 6825 6830 6835 6840 6845 6850 6855 6860 6865 6870 6875 6880 6885 6890 6895 6900 6905 6910 6915 6920 6925 6930 6935 6940 6945 6950 6955 6960 6965 6970 6975 6980 6985 6990 6995 7000 7005 7010 7015 7020 7025 7030 7035 7040 7045 7050 7055 7060 7065 7070 7075 7080 7085 7090 7095 7100 7105 7110 7115 7120 7125 7130 7135 7140 7145 7150 7155 7160 7165 7170 7175 7180 7185 7190 7195 7200 7205 7210 7215 7220 7225 7230 7235 7240 7245 7250 7255 7260 7265 7270 7275 7280 7285 7290 7295 7300 7305 7310 7315 7320 7325 7330 7335 7340 7345 7350 7355 7360 7365 7370 7375 7380 7385 7390 7395 7400 7405 7410 7415 7420 7425 7430 7435 7440 7445 7450 7455 7460 7465 7470 7475 7480 7485 7490 7495 7500 7505 7510 7515 7520 7525 7530 7535 7540 7545 7550 7555 7560 7565 7570 7575 7580 7585 7590 7595 7600 7605 7610 7615 7620 7625 7630 7635 7640 7645 7650 7655 7660 7665 7670 7675 7680 7685 7690 7695 7700 7705 7710 7715 7720 7725 7730 7735 7740 7745 7750 7755 7760 7765 7770 7775 7780 7785 7790 7795 7800 7805 7810 7815 7820 7825 7830 7835 7840 7845 7850 7855 7860 7865 7870 7875 7880 7885 7890 7895 7900 7905 7910 7915 7920 7925 7930 7935 7940 7945 7950 7955 7960 7965 7970 7975 7980 7985 7990 7995 8000 8005 8010 8015 8020 8025 8030 8035 8040 8045 8050 8055 8060 8065 8070 8075 8080 8085 8090 8095 8100 8105 8110 8115 8120 8125 8130 8135 8140 8145 8150 8155 8160 8165 8170 8175 8180 8185 8190 8195 8200 8205 8210 8215 8220 8225 8230 8235 8240 8245 8250 8255 8260 8265 8270 8275 8280 8285 8290 8295 8300 8305 8310 8315 8320 8325 8330 8335 8340 8345 8350 8355 8360 8365 8370 8375 8380 8385 8390 8395 8400 8405 8410 8415 8420 8425 8430 8435 8440 8445 8450 8455 8460 8465 8470 8475 8480 8485 8490 8495 8500 8505 8510 8515 8520 8525 8530 8535 8540 8545 8550 8555 8560 8565 8570 8575 8580 8585 8590 8595 8600 8605 8610 8615 8620 8625 8630 8635 8640 8645 8650 8655 8660 8665 8670 8675 8680 8685 8690 8695 8700 8705 8710 8715 8720 8725 8730 8735 8740 8745 8750 8755 8760 8765 8770 8775 8780 8785 8790 8795 8800 8805 8810 8815 8820 8825 8830 8835 8840 8845 8850 8855 8860 8865 8870 8875 8880 8885 8890 8895 8900 8905 8910 8915 8920 8925 8930 8935 8940 8945 8950 8955 8960 8965 8970 8975 8980 8985 8990 8995 9000 9005 9010 9015 9020 9025 9030 9035 9040 9045 9050 9055 9060 9065 9070 9075 9080 9085 9090 9095 9100 9105 9110 9115 9120 9125 9130 9135 9140 9145 9150 9155 9160 9165 9170 9175 9180 9185 9190 9195 9200 9205 9210 9215 9220 9225 9230 9235 9240 9245 9250 9255 9260 9265 9270 9275 9280 9285 9290 9295 9300 9305 9310 9315 9320 9325 9330 9335 9340 9345 9350 9355 9360 9365 9370 9375 9380 9385 9390 9395 9400 9405 9410 9415 9420 9425 9430 9435 9440 9445 9450 9455 9460 9465 9470 9475 9480 9485 9490 9495 9500 9505 9510 9515 9520 9525 9530 9535 9540 9545 9550 9555 9560 9565 9570 9575 9580 9585 9590 9595 9600 9605 9610 9615 9620 9625 9630 9635 9640 9645 9650 9655 9660 9665 9670 9675 9680 9685 9690 9695 9700 9705 9710 9715 9720 9725 9730 9735 9740 9745 9750 9755 9760 9765 9770 9775 9780 9785 9790 9795 9800 9805 9810 9815 9820 9825 9830 9835 9840 9845 9850 9855 9860 9865 9870 9875 9880 9885 9890 9895 9900 9905 9910 9915 9920 9925 9930 9935 9940 9945 9950 9955 9960 9965 9970 9975 9980 9985 9990 9995 10000 10005 10010 10015 10020 10025 10030 10035 10040 10045 10050 10055 10060 10065 10070 10075 10080 10085 10090 10095 10100 10105 10110 10115 10120 10125 10130 10135 10140 10145 10150 10155 10160 10165 10170 10175 10180 10185 10190 10195 10200 10205 10210 10215 10220 10225 10230 10235 10240 10245 10250 10255 10260 10265 10270 10275 10280 10285 10290 10295 10300 10305 10310 10315 10320 10325 10330 10335 10340 10345 10350 10355 10360 10365 10370 10375 10380 10385 10390 10395 10400 10405 10410 10415 10420 10425 10430 10435 10440 10445 10450 10455 10460 10465 10470 10475 10480 10485 10490 10495 10500 10505 10510 10515 10520 10525 10530 10535 10540 10545 10550 10555 10560 10565 10570 10575 10580 10585 10590 10595 10600 10605 10610 10615 10620 10625 10630 10635 10640 10645 10650 10655 10660 10665 10670 10675 10680 10685 10690 10695 10700 10705 10710 10715 10720 10725 10730 10735 10740 10745 10750 10755 10760 10765 10770 10775 10780 10785 10790 10795 10800 10805 10810 10815 10820 10825 10830 10835 10840 10845 10850 10855 10860 10865 10870 10875 10880 10885 10890 10895 10900 10905 10910 10915 10920 10925 10930 10935 10940 10945 10950 10955 10960 10965 10970 10975 10980 10985 10990 10995 11000 11005 11010 11015 11020 11025 11030 11035 11040 11045 11050 11055 11060 11065 11070 11075 11080 11085 11090 11095 11100 11105 11110 11115 11120 11125 11130 11135 11140 11145 11150 11155 11160 11165 11170 11175 11180 11185 11190 11195 11200 11205 11210 11215 11220 11225 11230 11235 11240 11245 11250 11255 11260 11265 11270 11275 11280 11285 11290 11295 11300 11305 11310 11315 11320 11325 11330 11335 11340 11345 11350 11355 11360 11365 11370 11375 11380 11385 11390 11395 11400 11405 11410 11415 11420 11425 11430 11435 11440 11445 11450 11455 11460 11465 11470 11475 11480 11485 11490 11495 11500 11505 11510 11515 11520 11525 11530 11535 11540 11545 11550 11555 11560 11565 11570 11575 11580 11585 11590 11595 11600 11605 11610 11615 11620 11625 11630 11635 11640 11645 11650 11655 11660 11665 11670 11675 11680 11685 11690 11695 11700 11705 11710 11715 11720 11725 11730 11735 11740 11745 11750 11755 11760 11765 11770 11775 11780 11785 11790 11795 11800 11805 11810 11815 11820 118



omit phase shifter 251 in favor of utilizing a baseband I and Q signal at mixers 221 and 222 respectively.

It should be appreciated that the frequency translation circuitry of the present invention may be utilized in a number of systems. For example, the signal quality of the above described preferred embodiment is suitable for use in cable television head end and/or video on demand type services.

Moreover, because of the reduced size, complexity, cost, and/or power requirements of the preferred embodiment frequency translator utilizing substantial circuit integration of the circuit elements, i.e., an upconverter on a "chip", embodiments of the present invention are uniquely adapted for deployment in configurations heretofore not possible. For example, frequency translators of the present invention may be deployed at neighborhood nodes of a cable television system to facilitate delivery of pay per view video or video on demand to select subscribers in the neighborhood. Additionally or alternatively, the ability to distribute frequency translation functionality throughout a communication system, such as the aforementioned cable television system, allows new and improved services to be offered. For example, highly directive communications, such as neighborhood advertisements, may be inserted on particular channels in particular areas.

Although the present invention and its advantages have been described in detail, it should be understood that various changes, substitutions and alterations can be made herein without departing from the spirit and scope of the invention as defined by the appended claims. Moreover, the scope of the present application is not intended to be limited to the particular embodiments of the process, machine, manufacture, composition of matter, means, methods and steps described in the specification. As one of ordinary skill in the art will readily appreciate from the disclosure of the present invention, processes, machines, manufacture, compositions of matter, means, methods, or steps, presently existing or later to be developed that perform substantially the same function or achieve substantially the same result as the corresponding embodiments described herein may be utilized according to the present invention. Accordingly, the appended claims are intended to include within their

